
875 Watt Pulse Start Lamp









Dia. =	4.6" (120mm)
MOL =	11.5" (292mm)
LCL =	7.0" (178mm)
Base =	Mogul (EX39)

MP 875W/BU/BT37/PS/740 GENERAL Characteristics ELECTRIC

Lamp Type	MH Pulse Start Single Ended
ANSI Code	M166/0
Bulb Shape	BT37
Base Type	Mogul (EX39)
Bulb Finish	Clear
Rated Life	26000 hours
Operating Position	Base Up ±15°

PHOTOMETRIC

Initial Lumens	98000	
Lumens Per Watt	112	
Lamp Lumen Depreciation (LLD)	0.80 (80%) @ 8000	
Correlated Color Temperature	4000K	
Chromaticity Coordinates (CIE-x,y)	.385 .390	
Color Rendering Index (CRI) R _a	68	

PHYSICAL

Bulb Diameter	4.6" (120mm)
Max. Overall Length (MOL)	11.5" (292mm)
Light Center Length (LCL)	7.0" (178mm)
Effective Arc Length	98.3mm
Max. Base Temperature (°C)	250
Max. Bulb Temperature (°C)	450
Socket Pulse Rating (KV)	4
Luminaire Type	Open / Enclosed Rated

ELECTRICAL

Lamp Watts	875
Lamp Oper. Voltage (Nom.)	250


<u>58953</u> Data shee


SUSTAINABILITY


Mercury Amount (mg)	107.5
Picograms of Hg per Mean Lumen Hour	53

NOTES

- Lamp performance ratings published in this data sheet are • based upon operation with magnetic ballasts.
- Operation of position-rated lamps outside of their tolerances • will result in poor performance.
- Minimum Starting Temperature: -40°C/°F.
- To calculate nighttime Scotopic lumens, multiply the lumen rating by the S/P ratio (1.7).
- Nominal color temperature rating is based on Vertical (\pm 15°) operation of the lamp. Off-vertical positions will result in higher color temperature.







(800) 451-2606

6675 Parkland Blvd., Suite 100 Solon, Ohio 44139 USA E-mail: Venture_Lighting@VentureLighting.com VentureLighting.com

THIS LAMP CONFORMS TO FEDERAL STANDARD 21 CFR 1040.30 Complies with (CE), Low Voltage (CE), WEEE and RoHS Directives

Warning: This lamp can cause skin burn and eye inflammation from shortwave ultraviolet radiation if outer envelope of the lamp is broken or punctured. Do not use where people will remain for more than a few minutes unless adequate shielding or other safety precautions are used. Lamps that will automatically extinguish when outer envelope is broken or punctured are commercially available.



Revision: 08/23/2022 #2193-11