




# Product Specification Bulletin

1500 Watt

HIGH WATT SINGLE ENDED

Clear - 4K

Mogul - Enclosed Luminaire  
EXTENDED LIFE



**MH 1500W/U/XL** **Product Number** **12342**

**Lamp Type** SINGLE ENDED METAL HALIDE

**ANSI Designation** M48/E

Performance Data	
<i>Light Output (Lumens @ 100 Hrs.)</i>	170000 V / 153000 H
<i>Lamp Lumens Per Watt</i>	113
<i>Mean Output (Lumens)</i>	136000
<i>Rated Life (Hrs. @ 5 Hr. / Start)</i>	6000 V / 3000 H
<i>Correlated Color Temperature K</i>	4000
<i>Chromaticity (CIE -X,Y)</i>	.385 .390
<i>Color Rendering Index (CRI)</i>	65
<i>Typical Warm Up Time (Minutes)</i>	3-5
<i>Typical Hot Restart Time (Minutes)</i>	10-15
<i>Burning Position</i>	UNIVERSAL

Physical Data / Requirements	
<i>Base Designation</i>	MOGUL (E39)
<i>Bulb Designation</i>	BT56
<i>Bulb Diameter</i>	7.0" (180mm)
<i>Max. Overall Length (MOL)</i>	15.3" (391mm)
<i>Light Center Length (LCL)</i>	9.5" (241mm)
<i>Effective Arc Length</i>	104.0 mm
<i>Max. Base Temperature (°C)</i>	250
<i>Max. Bulb Temperature (°C)</i>	430
<i>Luminaire Type</i>	ENCLOSED
<i>Socket Pulse Rating (KV)</i>	-
<i>Socket Style</i>	ENCLOSED RATED E39

Electrical Data / Requirements	
<i>Lamp Wattage</i>	1500
<i>Operating Voltage (Nominal)</i>	268
<i>Operating Current (Amps)</i>	6.2
<i>Min. Open Circuit Voltage (RMS)</i>	-
<i>Min. -Max. Starting Pulse (Peak V)</i>	-
<i>Min. Pulse Width At 2700 Volts (u sec)</i>	-
<i>Min. Pulse Rate Per 1/2 Cycle</i>	-
<i>Pulse Position (Min. % OCV Peak)</i>	-

**Revision:** 7/23/2008 **1469 - 7**

- Notes**
- ▶ Life shown is rated for 5 hours per start.
  - ▶ 80% Mean Lumen % refers to lamp performance under ideal conditions. The actual Mean Lumen range may be as much as 5% less.

**Lamps**

**THIS LAMP CONFORMS TO FEDERAL STANDARD 21 CFR 1040.30**  
**Warning: This lamp can cause skin burn and eye inflammation from shortwave ultraviolet radiation if outer envelope of the lamp is broken or punctured. Do not use where people will remain for more than a few minutes unless adequate shielding or other safety precautions are used. Lamps that will automatically extinguish when outer envelope is broken or punctured are commercially available.**